


Ceiling Mount Temperature, PIR Motion & Light Level Sensor

Part Number: ZW00471C



Features:

- 3 in 1 Sensor Module
- Simple and quick to install with sticky pads or screws
- Long battery life and battery level feedback
- Logging & Alarming for each sensor value

- The HALO multifunction sensor provides space temperature, PIR motion and light a single sensor
- The sensor is designed for application in home automation and light commercial environments
- Application can include: domestic, school, office & light commercial etc monitoring applications

	3V battery (CR123A/ 1700m Ah)
RF Distance	Min. 30M indoor 100M outdoor line of sight (subject to change due to environmental conditions such as walls, noise, materials etc.)
RF Frequency	868.4MH, 869.85MHz (EU)
Chip	Z Wave 500 series module
Battery Life	2-4 years (Depending on the trigger interval)
Detect Distance	8m (@FOV 0 deg, sensitivity 80) 4m (@FOV 90 deg, sensitivity 80)
Field of View	100 (+/- 10 deg)
Temperature	-10~40 °C (+/- 1.5 °C)
Illumination	0~30000Lux
Dimension	45.5Ø x49.3mm
Weight	55g
IP Classification	Indoor use
Operation Temperature	-10 ~ 40°C
Operation Humidity	85%RH max